Wang, L., Li, Y., Na, J., Gao, G., & Chen, Q. (2016). Nonlinear servo motion control based on unknown input observer. In *Proceedings of 2016 Chinese Intelligent Systems Conference* (Vol. II, pp. 541-550). (Lecture Notes in Electrical Engineering; Vol. 405). Springer Verlag. https://doi.org/10.1007/978-981-10-2335-4_49

Peer reviewed version

Link to published version (if available):

[10.1007/978-981-10-2335-4_49](https://doi.org/10.1007/978-981-10-2335-4_49)

[Link to publication record in Explore Bristol Research](#)

PDF-document

This is the author accepted manuscript (AAM). The final published version (version of record) is available online via Springer at http://link.springer.com/chapter/10.1007%2F978-981-10-2335-4_49. Please refer to any applicable terms of use of the publisher.

University of Bristol - Explore Bristol Research

General rights

This document is made available in accordance with publisher policies. Please cite only the published version using the reference above. Full terms of use are available: <http://www.bristol.ac.uk/red/research-policy/pure/user-guides/ebr-terms/>

Metadata of the chapter that will be visualized in SpringerLink

Book Title	Proceedings of 2016 Chinese Intelligent Systems Conference	
Series Title		
Chapter Title	Nonlinear Servo Motion Control Based on Unknown Input Observer	
Copyright Year	2016	
Copyright HolderName	Springer Science+Business Media Singapore	
Author	Family Name	Wang
	Particle	
	Given Name	Ligang
	Prefix	
	Suffix	
	Division	Faculty of Mechanical & Electrical Engineering
	Organization	Kunming University of Science & Technology
	Address	Kunming, 650500, China
	Email	
Author	Family Name	Li
	Particle	
	Given Name	Yunpeng
	Prefix	
	Suffix	
	Division	Faculty of Mechanical & Electrical Engineering
	Organization	Kunming University of Science & Technology
	Address	Kunming, 650500, China
	Email	
Corresponding Author	Family Name	Na
	Particle	
	Given Name	Jing
	Prefix	
	Suffix	
	Division	Faculty of Mechanical & Electrical Engineering
	Organization	Kunming University of Science & Technology
	Address	Kunming, 650500, China
	Email	najing25@163.com
Author	Family Name	Gao
	Particle	
	Given Name	Guanbin
	Prefix	
	Suffix	
	Division	Faculty of Mechanical & Electrical Engineering
	Organization	Kunming University of Science & Technology
	Address	Kunming, 650500, China
	Email	

Author	Email	
	Family Name	Chen
	Particle	
	Given Name	Qiang
	Prefix	
	Suffix	
	Division	College of Information Engineering
	Organization	Zhejiang University of Technology
	Address	Hangzhou, 310023, China
	Email	
Abstract	<p>This paper presents an alternative control method based on a new unknown input observer (UIO) for servo motor systems with unknown time-varying nonlinear dynamics and disturbances. By defining auxiliary filtered variables, an invariant manifold is derived and used to design the estimation of unknown dynamics. The new observer has only one scalar to be set, and thus can be easily incorporated into the control design to achieve precise output tracking. The convergence of the proposed estimator is compared with other three well-known schemes. Comparative simulation results show the satisfactory estimation and control performance.</p>	
Keywords (separated by '-')	Servo motion control - Unknown input observer - Nonlinear systems - Disturbance observer

Nonlinear Servo Motion Control Based on Unknown Input Observer

Ligang Wang, Yunpeng Li, Jing Na, Guanbin Gao and Qiang Chen

Abstract This paper presents an alternative control method based on a new unknown input observer (UIO) for servo motor systems with unknown time-varying nonlinear dynamics and disturbances. By defining auxiliary filtered variables, an invariant manifold is derived and used to design the estimation of unknown dynamics. The new observer has only one scalar to be set, and thus can be easily incorporated into the control design to achieve precise output tracking. The convergence of the proposed estimator is compared with other three well-known schemes. Comparative simulation results show the satisfactory estimation and control performance.

Keywords Servo motion control • Unknown input observer • Nonlinear systems • Disturbance observer

1 Introduction

Servo motors are a kind of widely used driving motors in the industry applications [1]. To achieve high precision motion control of such mechanisms, it is essential to derive accurate model of the whole systems. However, this is not a trivial task. In practical applications, the uncertainties that degrade the motion control performance include both internal and external disturbances such as friction, load, torque, and also modeling error. To handle such uncertainties and disturbances, there are two widely used approaches: adaptive control and disturbance observer. In the adaptive control framework, e.g., [2, 3], an important assumption is that the unknown

L. Wang · Y. Li · J. Na (✉) · G. Gao

Faculty of Mechanical & Electrical Engineering, Kunming University of Science & Technology, Kunming 650500, China
e-mail: najing25@163.com

Q. Chen

College of Information Engineering, Zhejiang University of Technology,
Hangzhou 310023, China

dynamics should be strictly reformulated as a linearly parameterized form. To relax this assumption, some functional approximators, e.g., neural network, fuzzy system, were further incorporated into the control synthesis of nonlinear servo motion mechanisms [4–6]. However, the function approximation is only valid for continuous functions in a compact set, and only semi-global stability can be proved.

In the past decades, disturbance observer (DOB) [7, 8] was also proposed, where the disturbances and modeling uncertainties are lumped as a time-varying disturbance, which is estimated using an observer. The traditional design methods of DOB are based on frequency domain techniques so that it cannot be extended to nonlinear systems [9]. In [7], a two-stage design procedure to improve disturbance attenuation ability of linear/nonlinear controllers is proposed. The DOB-based control can compensate the unparameterizable uncertainties, and has a simplified structure. In generic nonlinear DOB design, an observer has a similar structure to original system and there are several parameters to be set. In our recent work [10], we proposed a simply yet effective UIO to address the engine torque estimation. The convergence and robustness are also rigorously analyzed.

The aim of this paper is to exploit the idea of UIO proposed in [10] for the precision motion control of nonlinear servo systems with disturbances. First, we present the design of UIO based on available system variables to design the disturbance estimators. We also compare the estimation response of the proposed UIO to other three estimators, e.g., extended state observer (ESO) [11, 12], nonlinear disturbance observer (NDO) [13], and sliding model observer [14]. The proposed UIO is incorporated into the control design to alleviate the effects of these unknown dynamics, e.g., friction and disturbance. Comparative simulations are included to show the satisfactory control performance.

2 Problem Formulation

In this paper, the following servo motion system driven by a linear DC motor as [15] will be considered as follows:

$$\begin{cases} \dot{x}_1 = x_2 \\ \dot{x}_2 = (a\dot{x}_1 + u - f_f - f_r - f_l) / b \end{cases} \quad (1)$$

where u is the control voltage, x_1 , x_2 are the motor rotation position and speed; f_f is the friction force, f_r is the ripple force, and f_l is the applied load force. The parameters a , b denote the effect of mechanical and electrical dynamics, whose nominal values are available for most physical systems.

The objective of this paper is to introduce an alternative control scheme for system (1) in the presence of unknown dynamics f_f , f_r , f_l . In particular, the UIO proposed in [10] is modified to estimate and then compensate these unknown forces, which leads to a simple but efficient two-step control design procedure.

3 Disturbance Observer Design

We first consider the estimation of the unknown dynamics using the unknown input observer. Thus, we rewrite the second equation of the system (1) as

$$\dot{x}_2 = [ax_2 + u - F(x_1, x_2)] / b \quad (2)$$

where $F(x_1, x_2) = f_f + f_r + f_l$ is the lumped unknown dynamics.

This section first presents theoretical developments of a new input observer to estimate the unknown dynamics. Without loss of generality, we assume the derivative of $F(x_1, x_2)$ is bounded, i.e., $\sup_{t \geq 0} |\dot{F}(x_1, x_2)| \leq \hbar$ holds for a constant $\hbar > 0$.

A. Unknown Input Observer Design

We define the filtered variables x_{2f} , u_f of x_2 , u as

$$\begin{cases} k\dot{x}_{2f} + x_{2f} = x_2, & x_{2f}(0) = 0 \\ k\dot{u}_f + u_f = u, & u_f(0) = 0 \end{cases} \quad (3)$$

where $k > 0$ is a filter parameter.

An ideal invariant manifold [16] will be used to inspire the design of UIO.

Lemma 1 [10] Consider system (2) and filter operation (3), the variable

$$\beta = (x_2 - x_{2f}) / k - (ax_{2f} + u_f - F) / b \quad (4)$$

is ultimately bounded for any finite $k > 0$, and

$$\lim_{k \rightarrow 0} [\lim_{t \rightarrow \infty} \{(x_2 - x_{2f}) / k - (ax_{2f} + u_f - F) / b\}] = 0,$$

Proof We refer to [10] for a similar proof. $\diamond$

The above ideal invariant manifold provides a mapping from the filtered variables x_{2f} , u_f to the unknown dynamics F . Thus, it can be used to design an estimator for F without knowing any information of $\dot{x}_2$. Based on the invariant manifold, a feasible estimator of $F(x_1, x_2)$ is given by

$$\hat{F} = ax_{2f} + u_f - b(x_2 - x_{2f}) / k \quad (5)$$

Clearly, only the filter constant $k > 0$ should be selected by the designer.

The convergence property of the proposed observer can be summarized as

Theorem 1 For system (2) with unknown input observer (5), the estimation error $e_F = F - \hat{F}$ is bounded by $|e_F(t)| \leq \sqrt{e_F^2(0)e^{-t/k} + k^2 \hbar^2}$ and thus $F \rightarrow \hat{F}$ holds for $k \rightarrow 0$ or $\hbar \rightarrow 0$.

Proof We apply a low-pass filter $(\cdot)_f = [\cdot] / (ks + 1)$ on both sides of (2), so that

$$\frac{s}{ks+1} [x_2] = \frac{a}{b} \cdot \frac{1}{ks+1} [x_2] + \frac{1}{b} \cdot \frac{1}{ks+1} [u] - \frac{1}{b} \cdot \frac{1}{ks+1} [F] \quad (6)$$

We consider (6) together with the first equation of (3) and have

$$\dot{x}_{2f} = \frac{x_2 - x_{2f}}{k} = \frac{ax_{2f} + u_f - F_f}{b} \quad (7)$$

where F_f is the filtered version of F given by $k\dot{F}_f + F_f = F$. Then it follows from (5) and (7) that $\hat{F} = F_f$, that is, the estimator gives the filtered version of the unknown dynamics. In this case, we can prove that the estimation error can be small using sufficiently small k . For this purpose, we derive the estimation error as

$$e_F = F - \hat{F} = \left(1 - \frac{1}{ks+1}\right) F = \frac{ks}{ks+1} [F] \quad (8)$$

To facilitate the convergence proof, we further represent the estimation error (8) in the time-domain as

$$\dot{e}_F = \dot{F} - \dot{\hat{F}} = \dot{F} - \frac{1}{k} (F - F_f) = -\frac{1}{k} e_F + \dot{F} \quad (9)$$

Select a Lyapunov function as $V = \frac{1}{2} e_F^2$, then its derivative can be given as

$$\dot{V} = e_F \dot{e}_F = -\frac{1}{k} e_F^2 + e_F \dot{F} \leq -\frac{1}{k} V + \frac{k}{2} \dot{F}^2 \quad (10)$$

We can calculate the solution of (10) as $V(t) \leq e^{-t/k} V(0) + k^2 \dot{F}^2 / 2$, so $|e_F(t)| \leq \sqrt{e_F^2(0) e^{-t/k} + k^2 \dot{F}^2}$. In this case, one can verify that $e_F(t) \rightarrow 0$ for $k \rightarrow 0$ and/or $\dot{F} \rightarrow 0$. $\diamond$

B. Comparison to different disturbance estimation methods

In this subsection, we will compare the proposed UIO with other three estimators for system (2) to show their convergence and implementation.

B.1: Extended state observer (ESO)

ESO was initially proposed by Han in [11, 12], and has gained many applications [1]. The basic idea of ESO is to regard the lumped disturbances as a new state variable of the system, which can be estimated via a high-gain observer. Considering F as an extended state as $x_3 = F$, then the Eq. (2) can be rearranged as

$$\begin{cases} \dot{x}_2 = (ax_2 + u - F) / b \\ \dot{x}_3 = c(t) \end{cases} \quad (11)$$

where $c(t) = \dot{F}$ is assumed to be bounded. Thus we can design an ESO as

$$\begin{cases} \dot{z}_1 = -[z_2 - \beta_1(z_1 - x_2)] / b + u / b + ax_2 / b \\ \dot{z}_2 = -\beta_2(z_1 - x_2) \end{cases} \quad (12)$$

where β_1, β_2 are the feedback gains in the observer, z_1 is the estimation of x_2 and z_2 is the estimation of F . A feasible way to determine β_1, β_2 can be given as $s^2 + \beta_1 s + \beta_2 = (s + p)^2$, where $p > 0$. As analyzed in [17], if $\dot{F}$ is bounded, then $z_1 \rightarrow x_2$ and $z_2 \rightarrow F$ hold for $p \rightarrow \infty$. In this paper, to make a trade-off between the convergence and robustness, we set $p = 1000$ in the simulations. The induced high-gain of ESO leads to a potential peaking phenomena as shown in [17], which may degrade the transient control response when the estimated state z_2 is used.

B.2: Nonlinear disturbance observer (NDO)

The authors of [13] provide a nonlinear disturbance observer to estimate the unknown disturbances. From system (2), we know $F = -b\dot{x}_2 + ax_2 + u$. Then we let $L > 0$ as the observer gain, so that a *direct* DO with exponential convergence can be formulated as

$$\dot{\hat{F}} = -L\hat{F} + L(-b\dot{x}_2 + ax_2 + u) \quad (13)$$

However, the above DO requires *prior* knowledge of acceleration signal $\dot{x}_2$, which may not be available or measured in actual systems.

To address this issue, we design an auxiliary variable $z = \hat{F} + Lbx_2$, and then design the following NDO as

$$\begin{cases} \dot{\hat{F}} = z - Lbx_2 \\ \dot{z} = -Lz + L(ax_2 + u + Lbx_2) \end{cases} \quad (14)$$

Then the observer error is derived from (14) as

$$\dot{e}_F = \dot{F} - L(-z - ax_2 - u - Lbx_2 + b\dot{x}_2) = -L(F - \hat{F}) + \dot{F} = -Le_F + \dot{F} \quad (15)$$

It is interesting to find that the error dynamics of NDO shown in (15) are in the same form of that of the proposed UIO. Thus, it can be proved that the observer error e_F of (15) will converge to zero for $\dot{F} = 0$ and/or $L \rightarrow \infty$. Thus, the response of NDO is the same as UIO. However, no auxiliary variable needs to be defined in the proposed UIO.

B.3: Sliding mode observer (SMO)

We assume the disturbance $F(t)$ is bounded, i.e., $|F(t)| \leq \tilde{\lambda}(t)$ holds for $\tilde{\lambda}(t) > 0$. Then, we can define the following sliding mode observer

$$\dot{\hat{x}}_2 = \frac{1}{b} [ax_2 + u - \sigma \text{sign}(x_2 - \hat{x}_2)] \quad (16)$$

with a small positive constant $\sigma > \tilde{\lambda}(t)$.

Then the observer output error between (2) and (16) can be obtained as $e_f = x_2 - \hat{x}_2$, so that its derivative is

$$b\dot{e}_f = -F + \sigma \text{sign}(e_f) \quad (17)$$

Based on the sliding mode theory and the equivalent control method [14], we know that e_f will reach the sliding mode surface $e_f = 0$ in finite time, and thus $F = (\tilde{\lambda} + \sigma)\text{sign}(e_f)$ for any bounded disturbance F . However, a well-recognized issue in the sliding model observer is the chattering due to the signum function. To reduce the chattering, a low-pass filter is adopted to give the following estimator:

$$\hat{F} = \frac{1}{ks + 1} [\sigma \text{sign}(e_f)] \quad (18)$$

In this case, we can verify the estimator error of (18) is the same as (8). Consequently, the steady-state convergence response of the sliding mode observer (16) is comparable to those of UIO and NDO. However, the estimated dynamics may not be smooth although the high-frequency switching can be reduced by introducing the low-pass filter in (18). This will be further shown in simulations. Moreover, the upper bound $\tilde{\lambda}(t)$ of the unknown dynamics $F(t)$ should be known in the sliding mode observer design to determine the constant σ .

4 Control Design with Disturbance Observer

In this section, we will incorporate the proposed UIO into the control design for (1) to achieve output tracking for a given command x_{1d} . System (1) with the estimator (5) can be given as

$$\begin{cases} \dot{x}_1 = x_2 \\ \dot{x}_2 = \frac{1}{b} [ax_2 + u - \hat{F}(x_1, x_2) - e_f] \end{cases} \quad (19)$$

We define an auxiliary variable defined as

$$p = \dot{e} + k_2 e \quad (20)$$

where e is the tracking error as $e = x_1 - x_{1d}$, and k_2 is a positive constant.

Then we get the derivative of p as

$$\dot{p} = \ddot{e} + k_2 \dot{e} = [ax_2 + u - \hat{F}(x_1, x_2) - e_F] / b - \ddot{x}_{1d} + k_2 \dot{e} \quad (21)$$

The controller can be designed as

$$u = -k_1 p + \hat{F} - ax_2 - b(k_2 \dot{e} - \ddot{x}_{1d}) \quad (22)$$

where $k_1 > 0$ is the feedback gain.

Then the following theorem summarizes the main results of this paper:

Theorem 3 For the motor system (1), the controller (22) with the estimator (5) is designed. Then, for any unknown dynamics F , the estimation error e_F and the tracking error e will converge to a small compact set around zero, whose size depends on the bound $\sup_{t \geq 0} |\dot{F}| \leq \hbar$.

Proof Substituting (22) into (21), we have the tracking control error as

$$\dot{p} = \frac{1}{b} (-k_1 p - e_F) \quad (23)$$

Select a Lyapunov function as $V = \frac{1}{2}bp^2 + \frac{1}{2}e_F^2$, so that its time derivative can be calculated along as

$$\dot{V} = bp\dot{p} + e_F\dot{e}_F = -k_1 p^2 - pe_F - \frac{1}{k}e_F^2 + e_F\dot{F} \leq -\alpha V + \frac{\eta}{2}\hbar^2 \quad (24)$$

where $\alpha = \min \{2(k_1 - \eta/2)/b, 2(1/k - 1/\eta)\}$ is positive for $k_1 > \eta/2 > k/2$, $k > 0$. Thus, we can obtain from (24) that $V(t) \leq e^{-\alpha t}V(0) + \eta\hbar^2/(2\alpha)$ holds and this implies that p and e_F will exponentially converge to a compact set defined by $\Omega = \{p, e_F \mid |p| \leq \sqrt{\eta\hbar^2/\alpha b}, |e_F| \leq \sqrt{\eta\hbar^2/\alpha}\}$. $\diamond$

5 Simulations

This section will present comparative simulation results to demonstrate the validity of the proposed method, and to compare the estimation response of the above mentioned four estimators for F . The parameters of model (1) can be found in [15],

which lead to the lumped parameters $a = -123$, $b = 0.69$. Moreover, the ripple force is given by

$$f_r = A_r \sin(2\pi x_1 / P + \varphi) \quad (25)$$

where $\omega = 2\pi/P = 314$ and $\varphi = 0.05\pi$. The friction model is given as

$$f_f = \left[f_c + (f_s - f_c) e^{-(x_2 / \dot{x}_s)^2} \right] \text{sign}(x_2) + Bx_2 \quad (26)$$

where $f_s = 20$, $f_c = 10$, $\dot{x}_s = 0.1$, $B = 10$ define the effects of the maximum static friction, the coulomb friction the Stribeck effect and the viscous friction. Moreover, the external load is given as $f_l = 50 \sin(2\pi t)$. In the control design, the filter parameter is $k = 0.001$, and the feedback gains used in the controller are chosen as $k_1 = 2$, $k_2 = 500$.

Figure 1a shows the tracking responses of the motor position and speed using the presented control (22) with the proposed UIO. It is shown that fairly smooth and

Fig. 1 Simulation results: **a** Tracking control response of the proposed control (22) with (5); **b** Estimation performance of UIO (5), ESO (12), NDO (14) and SMO (18); **c** The zoom-in plot of (b); **d** Estimator errors of UIO (5), ESO (12), NDO (14) and SMO (18)

satisfactory control performance can be obtained. The profiles of the estimated disturbances are given in Fig. 1b, c. The first picture of Fig. 1b shows the estimation response of F using the four estimators, and its zoom-in view of the estimation between 0.2 and 0.3 s is shown in Fig. 1c. We can see the major trends of F can be accurately captured, although there is a small phase delay (about 0.001 s). This phase delay comes from the introduced low-pass filter (3). It is noted that k should be chosen as a trade-off between the estimation performance and robustness.

Moreover, we compare their estimation error responses in Fig. 1d. It can be found that the performance of NDO is indeed very similar to that of UIO, which are all better than that of ESO and SMO. In particular, the phase delay of NDO is smaller than that of ESO. Moreover, the implementation of the proposed UIO is simpler than that of ESO. On the other hand, as we stated in Sect. 3, SMO creates oscillated estimation results. The estimation errors of all these four different estimators shown in Fig. 1d further conform the above analysis.

6 Conclusion

In this paper, we propose a new nonlinear disturbance observer for servo mechanisms by extending the principle of a recently proposed unknown input observer. This new UIO has only one constant to be selected and a simpler structure, while its convergence response is comparable to that of generic NDO, ESO and SMO. The proposed estimator is incorporated into the feedback control design to achieve precision motion control. The closed-loop system stability including the UIO can be rigorously proved. Simulations are given to verify the theoretical analysis. The results demonstrate that the proposed UIO can achieve a superior estimation compared to ESO and SMO. Future work will focus on the robustness analysis for the proposed UIO and other estimators.

Acknowledgments This work is supported by National Natural Science Foundation of China (NSFC) under grant No. 61573174, 61433003.

References

1. Li S, Zong K, Liu H (2011) A composite speed controller based on a second-order model of permanent magnet synchronous motor system. *Trans Inst Meas Control* 33:522–541
2. Yao B, Xu L (2002) Adaptive robust motion control of linear motors for precision manufacturing. *Mechatronics* 12:595–616
3. Yang Z-J, Hara S, Kanae S, Wada K, Su C-Y (2010) An adaptive robust nonlinear motion controller combined with disturbance observer. *IEEE Trans Control Syst Technol* 18:454–462
4. Huang S, Tan KK, Lee TH (2002) Adaptive motion control using neural network approximations. *Automatica* 38:227–233

5. Na J, Chen Q, Ren X, Guo Y (2014) Adaptive prescribed performance motion control of servo mechanisms with friction compensation. *IEEE Trans Ind Electron* 61:486–494
6. Na J, Ren XM, Herrmann G, Qiao Z (2011) Adaptive neural dynamic surface control for servo systems with unknown dead-zone. *Control Eng Pract* 19:1328–1343
7. Chen W-H, Ballance DJ, Gawthrop PJ, O'Reilly J (2000) A nonlinear disturbance observer for robotic manipulators. *IEEE Trans Ind Electron* 47:932–938
8. Sariyildiz E, Ohnishi K (2015) Stability and robustness of disturbance-observer-based motion control systems. *IEEE Trans Ind Electron* 62:414–422
9. Chen W-H, Yang J, Guo L, Li S (2015) Disturbance observer-based control and related methods: an overview
10. Na J, Herrmann G, Burke R, Brace C (2015) Adaptive input and parameter estimation with application to engine torque estimation. In: 2015 54th IEEE conference on decision and control (CDC), pp 3687–3692
11. Jingqing H (1995) The “Extended State Observer” of a class of uncertain systems. *Control Decis* 1
12. Han J (2009) From PID to active disturbance rejection control. *IEEE Trans Ind Electron* 56:900–906
13. Liu ZL, Svoboda J (2006) A new control scheme for nonlinear systems with disturbances. *IEEE Trans Control Syst Technol* 14:176–181
14. Edwards C, Spurgeon S (1998) Sliding mode control: theory and applications. CRC Press, Boca Raton
15. Tan K, Huang S, Lee T (2002) Robust adaptive numerical compensation for friction and force ripple in permanent-magnet linear motors. *IEEE Trans Magnet* 38:221–228
16. Astolfi A, Ortega R (2003) Immersion and invariance: a new tool for stabilization and adaptive control of nonlinear systems. *IEEE Trans Autom Control* 48:590–606
17. Guo B-Z, Zhao Z-L (2011) On the convergence of an extended state observer for nonlinear systems with uncertainty. *Syst Control Lett* 60:420–430

Author Query Form

Book ID : 421067_1_En

Chapter No : 49

Springer

the language of science

Please ensure you fill out your response to the queries raised below and return this form along with your corrections

Dear Author

During the process of typesetting your chapter, the following queries have arisen. Please check your typeset proof carefully against the queries listed below and mark the necessary changes either directly on the proof/online grid or in the 'Author's response' area provided below

Query Refs.	Details Required	Author's Response
AQ1	No queries.	

MARKED PROOF

Please correct and return this set

Please use the proof correction marks shown below for all alterations and corrections. If you wish to return your proof by fax you should ensure that all amendments are written clearly in dark ink and are made well within the page margins.

<i>Instruction to printer</i>	<i>Textual mark</i>	<i>Marginal mark</i>
Leave unchanged	... under matter to remain	Ⓟ
Insert in text the matter indicated in the margin	⌵	New matter followed by ⌵ or ⌵ [Ⓢ]
Delete	/ through single character, rule or underline or ⌵ through all characters to be deleted	Ⓞ or Ⓞ [Ⓢ]
Substitute character or substitute part of one or more word(s)	/ through letter or ⌵ through characters	new character / or new characters /
Change to italics	— under matter to be changed	↙
Change to capitals	≡ under matter to be changed	≡
Change to small capitals	≡ under matter to be changed	≡
Change to bold type	~ under matter to be changed	~
Change to bold italic	≈ under matter to be changed	≈
Change to lower case	Encircle matter to be changed	≡
Change italic to upright type	(As above)	⌵
Change bold to non-bold type	(As above)	⌵
Insert 'superior' character	/ through character or ⌵ where required	Y or Y under character e.g. Y or Y
Insert 'inferior' character	(As above)	⌵ over character e.g. ⌵
Insert full stop	(As above)	⊙
Insert comma	(As above)	,
Insert single quotation marks	(As above)	Y or Y and/or Y or Y
Insert double quotation marks	(As above)	Y or Y and/or Y or Y
Insert hyphen	(As above)	⌵
Start new paragraph	┐	┐
No new paragraph	┐	┐
Transpose	┐	┐
Close up	linking ○ characters	○
Insert or substitute space between characters or words	/ through character or ⌵ where required	Y
Reduce space between characters or words		↑