



Guérin, P. A., Rubino, G., & Brukner, Č. (2019). Communication through quantum-controlled noise. *Phys. Rev. A*, 99(6), Article 062317. <https://doi.org/10.1103/PhysRevA.99.062317>

Publisher's PDF, also known as Version of record

Link to published version (if available):
[10.1103/PhysRevA.99.062317](https://doi.org/10.1103/PhysRevA.99.062317)

[Link to publication record in Explore Bristol Research](#)
PDF-document

This is the final published version of the article (version of record). It first appeared online via American Physical Society at <https://doi.org/10.1103/PhysRevA.99.062317>. Please refer to any applicable terms of use of the publisher.

University of Bristol - Explore Bristol Research

General rights

This document is made available in accordance with publisher policies. Please cite only the published version using the reference above. Full terms of use are available: <http://www.bristol.ac.uk/red/research-policy/pure/user-guides/ebr-terms/>

Communication through quantum-controlled noise

Philippe Allard Guérin,^{1,2} Giulia Rubino,¹ and Časlav Brukner^{1,2}

¹*Vienna Center for Quantum Science and Technology (VCQ), Faculty of Physics, University of Vienna, Boltzmanngasse 5, 1090 Vienna, Austria*

²*Institute for Quantum Optics and Quantum Information (IQOQI), Austrian Academy of Sciences, Boltzmanngasse 3, 1090 Vienna, Austria*



(Received 21 January 2019; published 17 June 2019)

In a recent series of works [Ebler *et al.*, *Phys. Rev. Lett.* **120**, 120502 (2018); [arXiv:1809.06655v2](#); [arXiv:1810.10457v2](#)], it has been shown that the quantum superposition of causal order—the quantum switch—offers an enhancement of classical and quantum channel capacity through noisy channels, a phenomenon that was coined “causal activation.” In this paper, we attempt to clarify the nature of the advantage, by comparing the quantum switch to a class of processes that can be interpreted as *quantum superposition of processes with the same causal order*. We show that some of these processes can match or even outperform the quantum switch at enhancing classical and quantum channel capacity, and argue that they require the same resources as the switch. We conclude, in agreement with Abbott *et al.* [[arXiv:1810.09826v1](#)], that the aforementioned advantages appear to be attributable to the ability to coherently control quantum operations, and not to indefinite causal order *per se*.

DOI: [10.1103/PhysRevA.99.062317](https://doi.org/10.1103/PhysRevA.99.062317)

I. INTRODUCTION

Quantum mechanics, as it is usually formulated, operates on a definite causal structure. There has been significant recent interest in investigating physically relevant situations in which the causal ordering between events is itself governed by quantum mechanics [1–4]. One interesting such causal structure is the quantum superposition of causal orders, also known as the *quantum switch* [3]. In the quantum switch, a quantum system controls the order of applications of two quantum channels: when the state of the control qubit is $|0\rangle$, the channel \mathcal{M}_A is applied on a target system before \mathcal{M}_B , while if the control qubit is $|1\rangle$, \mathcal{M}_B is applied before \mathcal{M}_A . The control qubit can be the path of a photon in an interferometer, but more exotic realizations where gravity plays a role have also been studied [5–7]. It has been established theoretically that the quantum switch offers various information processing advantages over causally ordered quantum mechanics [8–10], and there have been multiple experimental implementations of the switch [11–17]


More recently, a series of papers [18–20] have investigated the role of the switch in the context of classical and quantum Shannon information theory, and they have shown that the quantum switch offers advantages for enhancing channel capacity through noisy channels. All three tasks in Refs. [18–20] have the same basic structure:

- (1) Two *fixed* noisy channels $\mathcal{M}_A, \mathcal{M}_B$ are chosen.
- (2) A process—a bilinear supermap—turns these into a quantum channel $\mathcal{W}(\mathcal{M}_A, \mathcal{M}_B)$. The specific process that is considered is the quantum switch.
- (3) The information transmitting properties of \mathcal{W} are studied and it is concluded on these grounds that, for example, that “when the order of the communication channels in between them is a quantum degree of freedom, it can increase the

entanglement and enable transmission of quantum information beyond what was possible in a definite causal order” [19].

The effects described in Refs. [18,19] have been reproduced experimentally [15,17]. In Refs. [18,19], the authors are comparing the switch against a class of processes in which \mathcal{M}_A is applied, say, before \mathcal{M}_B , and there is no available “side channel” that could be used to transmit more information; in this paper we will call them *direct processes*. In Ref. [20], the authors also consider “independent channels in a superposition of alternative paths”; we comment on this in Appendix A.

Our work asks the question of whether there exists causally ordered processes, which are not direct processes, but which can be considered as resources equivalent to the switch. Indeed, any advantages that the switch might have in Shannon theory would disappear if we allowed ourselves to compare it against arbitrary causally ordered processes such as



where the two-qubit gate is a swap. On the one hand, one might rightfully object that the causally ordered process (1) lies outside the set of permitted processes since the sender makes use of a swap operation to directly transfer the information on a side channel which is not affected by the action of the two noisy channels. On the other hand, it is also important to keep a relatively large class of causally ordered processes against which the process under consideration can be compared; otherwise any advantage would be empty of practical significance.

Are the above-mentioned communication advantages offered by the quantum switch a mere consequence of the presence of a side channel similar to Eq. (1), or can they be

meaningfully attributed to indefinite causality? We attempt to address this question by defining a class of processes that includes the quantum switch, as well as conceptually similar causally ordered processes, but excludes the process of Eq. (1). We will formalize our discussion using the process matrix formalism, but equivalent definitions could be provided in other formalisms, for example with quantum combs [21] in the causally ordered case, or using the Kraus representations that were favored in Refs. [18–20].

II. PROCESS MATRICES

The process matrix formalism is a general framework for quantum mechanics that dispenses with the need to preassume a causal order between events. We quickly review the formalism here, and refer to the original references for a more complete introduction. A process matrix can be defined as a supermap [22] acting on local quantum channels [23]. To each local laboratory (or party) is associated an input Hilbert space \mathcal{H}_{A_i} and an output Hilbert space \mathcal{H}_{A_o} (here A is a label for the laboratory of Alice), with finite dimensions d_{A_i} and d_{A_o} respectively. A quantum channel $\mathcal{M}_A : \mathcal{L}(\mathcal{H}_{A_i}) \rightarrow \mathcal{L}(\mathcal{H}_{A_o})$ is a completely positive trace-preserving (CPTP) map, where $\mathcal{L}(\mathcal{H})$ denotes the space of linear operators on \mathcal{H} . It is convenient to define the Choi-Jamiołkowski (CJ) isomorphism [24], which associates to every quantum channel \mathcal{M} a corresponding quantum state

$$M^{A_i A_o} := \sum_{i,j=1}^{d_{A_i}} |i\rangle\langle j|^{A_i} \otimes \mathcal{M}(|i\rangle\langle j|)^{A_o}. \quad (2)$$

It will also be useful to define a “pure” version of the CJ isomorphism: if $K : \mathcal{H}_{A_i} \rightarrow \mathcal{H}_{A_o}$ is a linear map, then $|K\rangle\rangle^{A_i A_o} := \sum_{i=1}^{d_{A_i}} |i\rangle^i \otimes (K|i\rangle)^{A_o}$.

We define here process matrices in the bipartite case (Alice and Bob), its generalization to more parties is straightforward. Let $\mathcal{H}_P, \mathcal{H}_F$ be Hilbert spaces corresponding to the “past” and “future”, respectively. A process is a bilinear *supermap* that sends any pair of local quantum channels $\mathcal{M}_A, \mathcal{M}_B$, to a quantum channel $\mathcal{G}(\mathcal{M}_A, \mathcal{M}_B) : \mathcal{L}(\mathcal{H}_P) \rightarrow \mathcal{L}(\mathcal{H}_F)$. Mathematically, a process matrix is an operator $W \in \mathcal{L}(\mathcal{H}_P \otimes \mathcal{H}_{A_i} \otimes \mathcal{H}_{A_o} \otimes \mathcal{H}_{B_i} \otimes \mathcal{H}_{B_o} \otimes \mathcal{H}_F)$, such that

$$G^{PF} := \text{tr}_{A_i A_o B_i B_o} (W^{T_{A_i A_o B_i B_o}} \cdot M^{A_i A_o} \otimes M^{B_i B_o}), \quad (3)$$

is (the Choi operator of) a CPTP map from \mathcal{H}_P to \mathcal{H}_F whenever $M^{A_i A_o}$ and $M^{B_i B_o}$ represent CPTP maps. In Eq. (3), $T_{A_i A_o B_i B_o}$ designates the transposition on the spaces $\mathcal{H}_{A_i}, \mathcal{H}_{A_o}, \mathcal{H}_{B_i}, \mathcal{H}_{B_o}$ Hilbert spaces, while \mathcal{H}_P and \mathcal{H}_F are left untouched. A pure process [23] is a process such that G_{AB} is a unitary channel whenever $M^{A_i A_o}$ and $M^{B_i B_o}$ are unitary channels. It can be shown that all pure processes are rank-1 projectors $W = |w\rangle\langle w|$ [23].

In what follows we restrict our attention to cases where $d_{A_i} = d_{A_o} = d_{B_i} = d_{B_o} =: d$. We call W a *direct pure process* (in opposition to a process with side channels), if $d_F = d_P = d$, and the induced channel $\mathcal{G}(\mathcal{M}_A, \mathcal{M}_B)$ is

$$\text{---} \boxed{T} \text{---} \boxed{\mathcal{M}_A} \text{---} \boxed{U} \text{---} \boxed{\mathcal{M}_B} \text{---} \boxed{V} \text{---} \quad (4)$$

or

$$\text{---} \boxed{T} \text{---} \boxed{\mathcal{M}_B} \text{---} \boxed{U} \text{---} \boxed{\mathcal{M}_A} \text{---} \boxed{V} \text{---}, \quad (5)$$

for some fixed unitaries T, U, V . Such processes can be represented as rank-1 projectors: $W = |w\rangle\langle w|$. We will later consider $\mathcal{M}_A, \mathcal{M}_B$ noisy channels (e.g., depolarizing channels).

Definition 1: Superpositions of direct pure processes (SDPPs): Let $\{|w_i\rangle\rangle^{P A_i A_o B_i B_o F}\}_{i=1}^N$ be a collection of pure direct processes. Then the (equal) superposition of these processes is defined by $|w\rangle = \frac{1}{\sqrt{N}} \sum_i |i\rangle^C |w_i\rangle\rangle^{P A_i A_o B_i B_o F}$, which is a pure process with future Hilbert space $\mathcal{H}_C \otimes \mathcal{H}_F$. We call \mathcal{H}_C the control Hilbert space, and \mathcal{H}_F the target Hilbert space.

It is clear that the quantum switch $|w\rangle_{\text{switch}} = \frac{1}{\sqrt{2}} (|0\rangle^C | \mathbb{I} \rangle\rangle^{P A_i | \mathbb{I} \rangle\rangle^{A_o B_i | \mathbb{I} \rangle\rangle^{B_o F} + |1\rangle^C | \mathbb{I} \rangle\rangle^{P B_i | \mathbb{I} \rangle\rangle^{B_o A_i | \mathbb{I} \rangle\rangle^{A_o F})$ is a SDPP. However, it is also possible to take the superposition of two direct pure processes $|w_1\rangle$ and $|w_2\rangle$ with the *same causal order*, for example with A before B in both cases. It seems that any reasonable resource theory that contains the quantum switch—a superposition of direct pure processes with different causal orders—should also allow superpositions of direct pure processes with the same causal order. If some communication advantage is not a generic property of SDPPs, but only of those processes which are causally nonseparable [25–28], this would yield credence to the claim that the advantage is due to indefinite causality. We note that all SDPPs can be implemented using interferometric setups very similar to those used for implementing the switch in Refs. [11,12,14,16]; we will return to this point in the Discussion.

We now proceed to show that there are causally ordered SDPPs that match (or outperform) the quantum switch for all tasks of Refs. [18–20].

III. CLASSICAL AND QUANTUM COMMUNICATION

In Ref. [18], the authors consider two completely depolarizing channels: $\mathcal{M}_A(\rho) = \mathcal{M}_B(\rho) = \text{tr}(\rho) \frac{\mathbb{I}}{d}$. They find that placing these channels inside the switch allows for a nonzero classical channel capacity from \mathcal{H}_P to $\mathcal{H}_C \otimes \mathcal{H}_F$; if the target system has dimension 2, they lower bound the channel capacity by 0.049. Now consider the following two direct pure processes $|w_0\rangle = | \mathbb{I} \rangle\rangle^{P A_i | \mathbb{I} \rangle\rangle^{A_o B_i | \mathbb{I} \rangle\rangle^{B_o F}$ and $|w_1\rangle = | X \rangle\rangle^{P A_i | \mathbb{I} \rangle\rangle^{A_o B_i | \mathbb{I} \rangle\rangle^{B_o F}$, where X is the Pauli- X matrix, as well as their corresponding superposition $|w\rangle = \frac{1}{\sqrt{2}} (|0\rangle^C |w_0\rangle + |1\rangle^C |w_1\rangle)$. This process can be represented as the following circuit:

$$\begin{array}{c} |+\rangle \\ \bullet \\ \oplus \text{---} \boxed{\mathcal{M}_A} \text{---} \boxed{\mathcal{M}_B} \end{array} \quad (6)$$

where the two-qubit gate is a controlled-NOT gate from the control to the target qubit, and $|+\rangle = \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle)$. This circuit allows for perfect communication of one classical bit: when the initial target state is $|+\rangle$, the final state of the control is $|+\rangle$, while if the initial target state is $|-\rangle$, the final control state is $|-\rangle$. This is a manifestation of *phase kickback*, which has been identified as a unifying feature common to many

be distributed over internal and external degrees of freedom. While this restriction might serve the purpose of selecting the quantum switch out of all other possible SDPPs, it could be overly limiting if the goal is to understand the information-theoretical consequences of the fact that external degrees of freedom are also quantized.

Chiribella and Kristjánsson thus set out to rule out processes such as that of Eq. (6), which although (in our opinion) natural in the context of second-quantized information processing, trivialize the advantages claimed for the switch in Refs. [18–20]. They do so by first defining an encoding channel $\mathcal{E} : \mathcal{L}(\mathcal{H}_Q) \rightarrow \mathcal{L}(\mathcal{H}_M \otimes \mathcal{H}_P)$ of an abstract quantum system \mathcal{H}_Q into “path” \mathcal{H}_P and “message” \mathcal{H}_M degrees of freedom, and require it to satisfy a nonsignalling condition

$$\mathrm{tr}_M[\mathcal{E}(\rho)] = \mathrm{tr}_M[\mathcal{E}(\sigma)], \forall \rho, \sigma \in \mathcal{L}(\mathcal{H}_Q). \quad (8)$$

This nonsignalling requirement does not unambiguously achieve the goal of ruling out the undesired processes: consider once again the process at the right of Fig. 1. It is clear from this space-time diagram that the unitary X can equivalently be placed either before, simultaneously, or after the first application of \mathcal{M}_A (and similarly for the first application of \mathcal{M}_B). This already shows an ambiguity regarding whether X should be considered as part of the “encoding” or not. If we—as we do here—define the encoding to happen at time $t = 0$ in the space-time diagram, then the encoding is the same as for the switch: $\mathcal{E}(\rho) = \rho_M \otimes |+\rangle\langle +|_P$, and it is nonsignalling in the sense of Eq. (8). Just as it is ambiguous whether X is part of the encoding operation, it is also unclear whether it should be considered, in the language of Ref. [34], as a “repeater operation” (which is required to be nonsignalling from the internal to the external degrees of freedom) or as a “communication channel” (for which no such restriction applies). Repeater operations are defined as those parts of the quantum evolution that are not labeled as communication channels, but it is not obvious what criteria determine which of the two labels applies for a given operation.

Moreover, it is clear that both the switch and the SDPP in Fig. 1 require two spatial modes to be implemented. In neither case is it possible for a single spatial mode to be used to transmit information, since no information is extractable from a single mode after all the noisy channels have been applied. The only way to send information through either of these two processes is to prepare a quantum superposition of the two spatial modes, and to recombine them after the noisy channels in order to read out the information. This suggests that there is no fundamental difference, regarding their status as a resource for Shannon theory, between the quantum switch and causally ordered SDPPs, and therefore, that the activation of channel capacity cannot be unambiguously attributed to indefinite causal order. Judging from Fig. 1, a possible interpretation is that the counterintuitive channel capacities allowed by SDPPs are rather a consequence of the ability to delocalize noisy channels in space-time. This feature allows establishing correlations between the noise in the different arms of the interferometer, which can be useful in protecting against noise.

Finally, one might say that the arguments of this section only apply to a particular implementation, and that they do

not apply to the quantum switch, when seen as an abstract primitive. Indeed our arguments have shown that the notion of encoding depends on the implementation, and it is not a property of an abstract process matrix. The abstract way to know whether a process contains a “side channel” is to look at the reduced process [25], where Alice and Bob are traced out,

$$\begin{aligned} W_r &= \frac{1}{4} \mathrm{tr}_{A_I A_O B_I B_O} |w\rangle\langle w|_{\text{switch}} \\ &= \frac{1}{4} \mathbb{I}^{PCF} + \frac{1}{8} (|0\rangle\langle 1| + |1\rangle\langle 0|)^C \otimes |\mathbb{I}\rangle\langle\mathbb{I}|^{PF}. \end{aligned} \quad (9)$$

We see that in the case of the quantum switch, the reduced process W_r is a quantum channel which allows for direct communication from \mathcal{H}_P to $\mathcal{H}_C \otimes \mathcal{H}_F$, no matter what noisy operations are being applied at A and B . As means of comparison, the reduced process for the SDPP of Eq. (6) is

$$W'_r = \frac{1}{4} (\mathbb{I}^{PCF} + X^P \otimes X^C \otimes \mathbb{I}^F). \quad (10)$$

Thus if one accepts this abstract definition of a side channel, both the quantum switch and the process of Eq. (6) contain a side channel that allows direct signaling from P to F . We leave open the question of whether the two side channels should be considered equivalent, or whether they can be differentiated in a physically meaningful way.

V. CONCLUSION

References [18–20] have shown that the quantum switch allows for certain enhancements of classical and quantum channel capacity, when compared against a restricted class of causally ordered processes, and have coined the term *causal activation* for this phenomenon. In this paper, we have examined whether these advantages can be univocally attributed to indefinite causality, or whether there are causally ordered processes that offer the same advantages and can be considered as equivalent resources. We have found insufficient reasons to reject any process belonging to a class that we named *superpositions of direct pure processes*. Some of the processes belonging to that class are causally ordered, but can match—or outperform—the quantum switch at the proposed tasks. We have also shown that the Shor quantum error correcting code can be used to find an SDPP that protects against arbitrary Pauli errors on the target qubit. Thus, we suggest that “*controlled activation*” might be a more apt name for the above-mentioned phenomenon.

Our findings bear similarities with those of Ref. [35]. In that work, an enhancement of channel capacity through quantum-controlled noisy channels is also found to be possible without indefinite causal order. However, the controlled-noise operations of Ref. [35] are not process matrices, and thus their results depend on the specific implementation of the noisy channels. Our results, however, as those of Refs. [18–20], are about process matrices and are independent of the way in which the noise is implemented. We elaborate on these comments in Appendix A.

Let us conclude with an attempt at interpreting the difference between the previously discussed tasks and other information processing tasks for which only an indefinite causal order yields an advantage [8–10,36]. A possible explanation for why there are causally ordered SDPPs that display a

This example shows that SDPPs (if one puts no limit on the number of control qubits) can be used to perfectly send one qubit of information, essentially trivializing the

problem of enhancing quantum and classical channel capacity if one were to take the set of all SDPPs as a resource.

-
- [1] L. Hardy, Probability theories with dynamic causal structure: A new framework for quantum gravity, [arXiv:gr-qc/0509120v1](#).
- [2] L. Hardy, Quantum gravity computers: on the theory of computation with indefinite causal structure, in *Quantum Reality, Relativistic Causality, and Closing the Epistemic Circle: Essays in Honour of Abner Shimony* (Springer, Dordrecht, 2009), pp. 379–401.
- [3] G. Chiribella, G. M. D’Ariano, P. Perinotti, and B. Valiron, Quantum computations without definite causal structure, *Phys. Rev. A* **88**, 022318 (2013).
- [4] O. Oreshkov, F. Costa, and Č. Brukner, Quantum correlations with no causal order, *Nat. Commun.* **3**, 1092 (2012).
- [5] M. Zych, F. Costa, I. Pikovski, and Č. Brukner, Bell’s Theorem for temporal order, [arXiv:1708.00248v2](#).
- [6] A. Dimić, M. Milivojević, D. Gočanin, and Č. Brukner, Quantum switch via Rindler observers, [arXiv:1712.02689v2](#).
- [7] P. A. Guérin and Časlav Brukner, Observer-dependent locality of quantum events, *New J. Phys.* **20**, 103031 (2018).
- [8] G. Chiribella, Perfect discrimination of no-signalling channels via quantum superposition of causal structures, *Phys. Rev. A* **86**, 040301(R) (2012).
- [9] M. Araújo, F. Costa, and Č. Brukner, Computational Advantage from Quantum-Controlled Ordering of Gates, *Phys. Rev. Lett.* **113**, 250402 (2014).
- [10] P. A. Guérin, A. Feix, M. Araújo, and Č. Brukner, Exponential Communication Complexity Advantage from Quantum Superposition of the Direction of Communication, *Phys. Rev. Lett.* **117**, 100502 (2016).
- [11] L. M. Procopio, A. Moqanaki, M. Araújo, F. Costa, I. Alonso Calafell, E. G. Dowd, D. R. Hamel, L. A. Rozema, Č. Brukner, and P. Walther, Experimental superposition of orders of quantum gates, *Nat. Commun.* **6**, 7913 (2015).
- [12] G. Rubino, L. A. Rozema, A. Feix, M. Araújo, J. M. Zeuner, L. M. Procopio, Č. Brukner, and P. Walther, Experimental verification of an indefinite causal order, *Sci. Adv.* **3**, e1602589 (2017).
- [13] G. Rubino, L. A. Rozema, F. Massa, M. Araújo, M. Zych, Č. Brukner, and P. Walther, Experimental entanglement of temporal orders, [arXiv:1712.06884v3](#).
- [14] K. Goswami, C. Giarmatzi, M. Kewming, F. Costa, C. Branciard, J. Romero, and A. G. White, Indefinite Causal Order in a Quantum Switch, *Phys. Rev. Lett.* **121**, 090503 (2018).
- [15] K. Goswami, J. Romero, and A. G. White, Communicating via ignorance, [arXiv:1807.07383v2](#).
- [16] K. Wei, N. Tischler, S.-R. Zhao, Y.-H. Li, J. M. Arrazola, Y. Liu, W. Zhang, H. Li, L. You, Z. Wang, Y.-A. Chen, B. C. Sanders, Q. Zhang, G. J. Pryde, F. Xu, and J.-W. Pan, Experimental Quantum Switching for Exponentially Superior Quantum Communication Complexity, *Phys. Rev. Lett.* **122**, 120504 (2019).
- [17] Y. Guo, X.-M. Hu, Z.-B. Hou, H. Cao, J.-M. Cui, B.-H. Liu, Y.-F. Huang, C.-F. Li, and G.-C. Guo, Experimental investigating communication in a superposition of causal orders, [arXiv:1811.07526v1](#).
- [18] D. Ebler, S. Salek, and G. Chiribella, Enhanced Communication with the Assistance of Indefinite Causal Order, *Phys. Rev. Lett.* **120**, 120502 (2018).
- [19] S. Salek, D. Ebler, and G. Chiribella, Quantum communication in a superposition of causal orders, [arXiv:1809.06655v2](#).
- [20] G. Chiribella, S. S. B. M. Banik, T. Guha, M. Alimuddin, A. Roy, S. Saha, S. Agrawal, and G. Kar, Indefinite causal order enables perfect quantum communication with zero capacity channel, [arXiv:1810.10457v2](#).
- [21] G. Chiribella, G. M. D’Ariano, and P. Perinotti, Theoretical framework for quantum networks, *Phys. Rev. A* **80**, 022339 (2009).
- [22] G. Chiribella, G. M. D’Ariano, and P. Perinotti, Transforming quantum operations: Quantum supermaps, *Europhys. Lett.* **83**, 30004 (2008).
- [23] M. Araújo, A. Feix, M. Navascués, and Č. Brukner, A purification postulate for quantum mechanics with indefinite causal order, *Quantum* **1**, 10 (2017).
- [24] M.-D. Choi, Completely positive linear maps on complex matrices, *Linear Algebra Appl.* **10**, 285 (1975).
- [25] M. Araújo, C. Branciard, F. Costa, A. Feix, C. Giarmatzi, and Č. Brukner, Witnessing causal nonseparability, *New J. Phys.* **17**, 102001 (2015).
- [26] O. Oreshkov and C. Giarmatzi, Causal and causally separable processes, *New J. Phys.* **18**, 093020 (2016).
- [27] C. Branciard, Witnesses of causal nonseparability: an introduction and a few case studies, *Sci. Rep.* **6**, 26018 (2016).
- [28] J. Wechs, A. A. Abbott, and C. Branciard, On the definition and characterisation of multipartite causal (non)separability, *New J. Phys.* **21**, 013027 (2019).
- [29] R. Cleve, A. Ekert, C. Macchiavello, and M. Mosca, Quantum algorithms revisited, *Proc. R. Soc. London, Ser. A* **454**, 339 (1997).
- [30] P. W. Shor, Scheme for reducing decoherence in quantum computer memory, *Phys. Rev. A* **52**, R2493 (1995).
- [31] M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information: 10th Anniversary Edition*, 10th ed. (Cambridge University Press, New York, 2011).
- [32] A. Steane, Multiple-particle interference and quantum error correction, *Proc. R. Soc. London, Ser. A* **452**, 2551 (1996).
- [33] O. Oreshkov, On the whereabouts of the local operations in physical realizations of quantum processes with indefinite causal order, [arXiv:1801.07594](#).
- [34] G. Chiribella and H. Kristjánsson, A second-quantised Shannon theory, [arXiv:1812.05292v1](#).
- [35] A. A. Abbott, J. Wechs, D. Horsman, M. Mhalla, and C. Branciard, Communication through coherent control of quantum channels, [arXiv:1810.09826v1](#).
- [36] M. Araújo, A. Feix, F. Costa, and Č. Brukner, Quantum circuits cannot control unknown operations, *New J. Phys.* **16**, 093026 (2014).
- [37] D. K. L. Oi, Interference of Quantum Channels, *Phys. Rev. Lett.* **91**, 067902 (2003).